



Lighting Your Life Since 1970

## Product Specifications - 87904SA

Job Name:	Job Type:
Quantity:	Comments:



### 87904SA

#### CounterMax MX-L 20" LED Under Cabinet Light

Uses MXInterLink2 accessories. Click [here](#) for a complete list of compatible accessories.

#### Finish

Satin Aluminum

#### Glass/Shade

#### Product Category

Under Cabinet Kit

#### Lamping

Number of Bulbs	4
Light Type	LED
Bulb Type	LED
Max Bulb Wattage	1
Max Fixture Wattage	4
Rated Life	±50,000 Hours
Rated Lumens	±320
Color Temp	±3,000 K
Bulb(s)	Integrated
Light Up/Down	N/A
Beam Spread	120
CRI	78-80
Photo Cell Included	N/A
Ballast/Driver/Transformer	No
Dimmable	No

#### Measurements

Width	2.0"
Height	1.0"
Length	20.0"
Extension	N/A
Back Plate Width	N/A
Back Plate Height	N/A
HCO	N/A
Min Overall Height	N/A
Max Overall Height	N/A
Hanging Weight	1.0 lbs
Height Adjustable	N/A
Slope	N/A
Chain Length	N/A
Wire Length	N/A
Canopy Width	N/A
Canopy Height	N/A
Canopy Length	N/A

#### Shipping

Carton Weight	1.0 lbs
Carton Width	3"
Carton Height	2"
Carton Length	26"
Carton Cubic Feet	0.11
Master Pack	6
Master Pack Weight	7.7 lbs
Master Pack Width	26.8"
Master Pack Height	7.9"
Master Pack Length	8.7"
Master Cubic Feet	1.06
UPS Shippable	Yes

#### Certification

Safety Rating	Dry
Energy Star	No
CA Title 24	No
CA Title 20	No
ADA	No
Dark Sky	N/A

#### Other

UPC Code	783209064522
Shades Included	N/A
Crystals Included	N/A
Diffuser Included	N/A
Conversion Kit	N/A
Material	Aluminum

#### Equivalents

Incandescent Watts	29.09
Fluorescent Watts	6.4

Maxim Lighting International and all designs, logos and images © 2013 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.