

*****READ & SAVE THESE INSTRUCTIONS *****
ACCESS LIGHTING
MODEL 20368MG
INSTALLATION & OPERATION INSTRUCTIONS

(1) TOOLS AND MATERIALS REQUIRED

- ❖ BLADE SCREW DRIVER
- ❖ WIRE CUTTERS
- ❖ WIRING SUPPLIES AS REQUIRED BY ELECTRICAL CODE

Attention:

Before assembling your lighting fixture, please read the following instructions. If you feel you do not have sufficient electrical experience, refer to a do-it-yourself wiring handbook or have your fixture installed by a qualified licensed electrician.

(2) GENERAL

1. To ensure the success of the installation, be sure to read these instructions and review the diagrams thoroughly before beginning.
2. All electrical connections must be in accordance with local codes, ordinances, or the National Electrical Code. If you are unfamiliar with methods of installing electrical wiring, secure the services of a qualified licensed electrician.
3. These fixtures are intended for mounting to a standard 4" x 2 1/4" deep metal octagon outlet box. The box must be directly supported by the building structure and U.L. Recognized.
4. Before commencing with the installation, **disconnect the power by turning off the circuit breaker** or by removing the fuse at the fuse box. Turning the power off using the light switch is not sufficient to prevent electrical shock.

NOTE:

The important safeguards and instructions appearing in this manual are not meant to cover all possible conditions and situations that may occur. It must be understood that common sense, caution and care, are factors that cannot be built into any product. These factors must be supplied by the person(s) caring for and operating the fixture.

(3) UNPACKING THE FIXTURE

On checking the contents of the box you will find;

- ❖ Fixture Back Plate
- ❖ Mounting Hardware
- ❖ Fixture Canopy with socket attached
- ❖ 2 x Glass Shades
- ❖ 1 x Gasket
- ❖ 2 x 18W FT18D Lamp (2G11 Base)

(4) PREPARE THE FIXTURE

Refer to attached illustration of fixture parts and assembly.

1. If you are replacing an existing fixture disconnect and remove the old fixture. Expose the supply wiring from the outlet box.
2. Secure the **Fixture Back Plate** to the junction box with the supplied **Mounting Screws (1)**.
3. Ensure that the supplied Large Square Gasket is securely fitted onto the Fixture Canopy with socket attached.
4. Pull the Supply wires through the Center Hole in the **Back Plate**.
5. Connect the **Black Supply Wire** to the **Black Wire** of the fixture with supplied **Wire Nuts (2)** ensuring a secure connection.
6. Connect the **White Supply Wire** to the **White Wire** from the fixture and secure with supplied **Wire Nuts (2)**.
7. Attach the **ground (GREEN) wire** from the fixture to the **outlet box ground terminal** (or to the box ground wire).
8. Secure all wire nuts connections with **UL listed electrical tape. Tuck wires carefully into Junction box.**
9. Position the **Fixture Canopy with Socket attached**, such that the 4 Screws protruding from the **Fixture Back Plate** align with the four designated holes in the **Fixture Canopy**. Place the supplied **Mini Circular Gaskets** onto each screw and then secure with the supplied **Knobs (3)**
10. Insert the specified **bulbs- 2 x 18w FT18DL (4)**. At the top of the fixture and one below.

DO NOT EXCEED WATTAGE SPECIFIED ON WARNING LABEL

11. Fit the **Glass Diffusers (5)** over the bulbs Secure by screwing into the threaded metal portion of the fixture housing the socket
12. **NOTE: Outdoor wall fixtures must be caulked with suitable PTV or silicone compound around the top and sides of the cover plate to reduce the chance of water entering into the splicing area.**
13. Restore electricity and check the operation of your new lighting fixture.

CAUTION:

- **Ensure that the Fitting is Cool and Switched off, Before Changing the Bulb.**
- **Do Not use Bulbs Exceeding Maximum Wattage, As Per Caution Label.**
- **Do not operate your fixture on or near any combustible material.**

MODEL 20368MG

