

access

LIGHTING

Read & Save these Instructions Model: 20389 Installations & Operation Instructions

1) TOOLS AND MATERIALS REQUIRED

- ❖ Blade Screwdriver
- ❖ Star Screwdriver
- ❖ Wire Cutters
- ❖ Wiring supplies as required by Electrical Code
- ❖ 2 x 75w PAR-30 (E-26 Base) Bulb

Attention:

Before assembling your lighting fixture, please read the following instructions.

(2) GENERAL

1. To ensure the success of the installation, be sure to read these instructions thoroughly before beginning.
2. All electrical connections must be in accordance with local codes, ordinances, or the National Electrical Code. If you are unfamiliar with methods of installing electrical wiring, secure the services of a qualified licensed electrician.
3. These fixtures are intended for mounting to a standard 4" x 2 1/4" deep metal octagon outlet box. The box must be directly supported by the building structure and U.L. Recognized.
4. Before commencing with the installation, **disconnect the power by turning off the circuit breaker** or by removing the fuse at the fuse box. Turning the power off using the light switch is not sufficient to prevent electrical shock.

NOTE:

The important safeguards and instructions appearing in this manual are not meant to cover all possible conditions and situations that may occur. It must be understood that common sense, caution and care, are factors that cannot be built into any product. The person(s) caring for and operating the fixture must supply these factors.

(3) UNPACKING THE FIXTURE

On checking the contents of the box you will find;

1. Fixture assembly
2. Hardware packet
3. Rubber Gasket
4. Universal Plate

CAUTION:

- **Ensure that the Fitting is Cool and Switched off, Before Changing Bulbs.**
- **Do Not use Bulbs Exceeding Maximum Wattage as Per Caution Label.**
- **Do Not Touch the Bulb while fixture is in operation**
- **Do not place the fixture on or near combustible material**

(4) PREPARE THE FIXTURE

1. If you are replacing an existing fixture, disconnect and remove the old fixture. Expose the supply wiring from the **j-box** and pass the wire through the designated hole in the **Universal Plate, Rubber Gasket and Fixture Back Plate.**
2. Lay the un-assembled fixture on a soft surface and carefully remove all the packing material.
3. Mount the **Universal Plate, Rubber Gasket and Fixture Back Plate** with the **Supplied Screws.**
4. Unscrew the two **Screws** on the top and underneath the fixture, that are securing the **Glass Covers** to the fixture. Insert **1 x 75w PAR-30 (E-26 Base) Bulb** into each socket.

DO NOT EXCEED THE RECOMMENDED WATTAGE.

5. Replace the **Glass Covers** and secure with the supplied **Screws.**
6. Connect the **Black Wire** from the fixture to the **Black Supply Wire** and the **White Fixture Wire** to the **White Supply Wire**, fasten securely with supplied **Wire Nuts** and secure **Wire Nuts** with **UL listed electrical tape** (not supplied).
7. Connect the **Green Ground Wire** from the fixture to the **Electrical Supply Ground Wire** and secure wire connections with supplied **Wire Nuts**, or attach the Ground Wire directly to the **Ground Screw** on the **Universal Plate**. Tuck all wires carefully into the **Fixture Back Plate.**
8. **Place the Fixture Canopy over the Fixture Back Plate;** such that the fixture is flush against the wall. Insert the supplied screws into the supplied holes in the **Fixture Canopy**, such that the screws fit into the **indented area on the Universal Plate.**

NOTE: This fixture has been Certified, For Wet Location, and is for outside applications. Therefore to reduce the risk of electrical shock it is strongly recommended that a silicone caulking be utilized to provide a watertight seal between the fixture and its mounting surface.

9. Restore electricity and turn on light.

access

LIGHTING

Read & Save these Instructions
Model: 20389
Installations & Operation Instructions

