

- 1 - CounterMax MX-LD-R LED Disc
- 2 - Connecting Cord
- 3 - 6-Way Distribution Hub
- 4 - 12V 2A Driver


### Surface Mount Installation

**Step One**




*Using hands, separate outer aluminum shell from LED lamp.*

**Step Two**



*Using included hardware and a screw driver, secure outer aluminum shell to cabinet surface*

**Step Three**



*Feed connecting cord through a pre-drilled hole in the cabinet surface or through the cut-out of the outer aluminum shell. Secure LED lamp into outer aluminum shell.*


### Recessed Installation

**Step One**




*Using hands, separate outer aluminum shell from LED lamp.*

**Step Two**



*Cut out from the bottom of the cabinet a hole using a 2.5" hole saw.*

**Step Three**



*Feed connecting cord through the hole in cabinet and secure LED lamp.*

### Optional Accessories

- E53850-AL Single MX-LD-R LED Disc Aluminum Finish
- E53850-BRZ Single MX-LD-R LED Disc Bronze Finish
- E53850-WT Single MX-LD-R LED Disc White Finish
- E53812-BK Motion Sensor
- E53811-BK Touch Dimmer Black
- E53811-WT Touch Dimmer White
- E53807-BK 24" Connecting Cord Black
- E53807-WT 24" Connecting Cord White
- E53809-BK 48" Connecting Cord Black
- E53809-WT 48" Connecting Cord White

*\*Can add an additional 3 MX-LD-R LED Discs for a total of 6 MX-LD-R LED Disc*