


①	②	③	④	⑤	⑥	⑦	⑧	⑨
Required Crystals Qty. : 1	1	24	3	3	3	6	6	6
Extra Crystals Qty. : 0	0	3	0	0	0	1	1	1
Extra Hooks Qty. : 13								

Required Crystals Qty. :

Extra Crystals Qty. :

Extra Hooks Qty. :



## IMPORTANT TURN OFF THE POWER AT THE MAIN FUSE OR CIRCUIT BREAKER BOX BEFORE STARTING INSTALLATION

**Carefully unpack and identify all parts before assembly. Bulbs are not included.**

1. Spread open all arms so they are evenly spaced apart to each other.
2. Lock lower tier arms by fastening with cap screw onto center body.
3. Slip leaf and cover (with notches) through threaded end of center pipe. Then slip same end of pipe through round plate located at top section of fixture. Make certain arms are locked onto the cover notches. Secure all together from below by slipping another cover (without notches) and fastening with cap nut.
4. Install curl assembly by screwing into middle of fixture.
5. Follow enclosed supplement installation instructions for electrical and fixture installation onto house outlet box. If you do not have an outlet box at desired location to attach the fixture than hire a qualified electrician to create one.
6. Install lower leaf assembly by screwing onto bottom of fixture.
7. Install bobèches by slipping through socket until it securely sits onto fitter.
8. Slip candle tube over sockets.
9. Install bulbs (not included). See relamping label located near socket area for type and maximum allowed wattage.
10. Hang all crystal glass parts as shown on drawing. NOTE: To replace broken crystals extras are included in hardware bag. Replace by gently bending open pin, remove broken crystal, hook new one, then close back pin. Avoid bending pin into sharp angle.