



## Product Specifications for E53800-BRZ

Job Name:	Job Type:
Quantity:	Comments



### E53800-BRZ

#### CounterMax MX-LMC LED Mini Channel Starter Kit

Includes: (A) Four 10" CounterMax MX-LMC LED mini channels (B) One 100-240V input, 12V 2A output driver with 72" output cord (C) One 6" power supply cord (D) Two 2" connecting cords (E) Eight flat mounting clips (F) Eight 45 degree angle mounting clips (G) Mounting screws (H) End caps. Optional Accessories: (A) Motion Sensor E53812-BK (B) Touch Dimmer E53811-BK WT. Uses MXInterLink6 accessories. Click [here](#) for a complete list of compatible accessories.

#### Finish

Anodized Bronze

#### Glass/Shade

Clear

#### Product Category

Under Cabinet Kit

#### Lamping

Number of Bulb(s)	96
Light Type	LED
Bulb Type	LED
Max Bulb Wattage	0.08
Max Fixture Wattage	7.68
Rated Life	±50,000 Hours
Rated Lumens	±520
Color Temp	±3,000 K
Bulb(s) Included	Integrated
Light Up/Down	N/A
Beam Spread	N/A
CRI	N/A
Photo Cell Included	N/A
Ballast/Driver/Transformer	No
Dimmable	Optional Touch Dimmer

#### Measurements

Width	0.38"
Height	0.38"
Length	50.00"
Extension	N/A
Back Plate Width	N/A
Back Plate Height	N/A
HCO	N/A
Min Overall Height	N/A
Max Overall Height	N/A
Hanging Weight	0.74 lb(s)
Height Adjustable	N/A
Slope	N/A
Chain Length	N/A
Wire Length	N/A
Canopy Width	N/A
Canopy Height	N/A
Canopy Length	N/A

#### Shipping

Carton Weight	0.85 lb(s)
Carton Width	5.31"
Carton Height	2.24"
Carton Length	14.56"
Carton Cubic Feet	N/A
Master Pack	20
Master Pack Weight	19.14 lb(s)
Master Pack Width	14.76"
Master Pack Height	11.02"
Master Pack Length	15.11"
Master Cubic Feet	N/A
UPS Shippable	Yes

#### Certification

Safety Rating	Dry
Energy Star	No
CA Title 24	No
CA Title 20	No
ADA	No

#### Other

UPC Code	845094050346
Material	Aluminum

#### Equivalents

Incandescent Watts	47.27
Fluorescent Watts	10.4

ET2 Contemporary Lighting and all designs, logos and images © 2014 ET2 Contemporary Lighting. All Rights Reserved. ET2 Contemporary Lighting reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes. Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.