



Product Specifications for E53804-BRZ

Job Name:	Job Type:
Quantity:	Comments:



E53804-BRZ

CounterMax MX-LMC LED Mini Channel Add-On Kit

Note: This is an add-on kit and does not include a power supply. Includes: (A) Two 10" CounterMax MX-LMC LED mini channels (B) Two 5" CounterMax MX-LMC LED mini channels (C) Eight flat mounting clips (D) Eight 45 degree angle mounting clips (G) Mounting screws (H) End caps. Uses MXInterLink6 accessories. Click [here](#) for a complete list of compatible accessories.

Finish

Anodized Bronze

Glass/Shade

Clear

Product Category

Under Cabinet Kit

Lamping

Number of Bulb(s)	72
Light Type	LED
Bulb Type	LED
Max Bulb Wattage	0.08
Max Fixture Wattage	5.76
Rated Life	±50,000 Hours
Rated Lumens	±390
Color Temp	±3,000 K
Bulb(s) Included	Integrated
Light Up/Down	N/A
Beam Spread	N/A
CRI	N/A
Photo Cell Included	N/A
Ballast/Driver/Transformer	No
Dimmable	Optional Touch Dimmer

Measurements

Width	0.38"
Height	0.38"
Length	30.00"
Extension	N/A
Back Plate Width	N/A
Back Plate Height	N/A
HCO	N/A
Min Overall Height	N/A
Max Overall Height	N/A
Hanging Weight	0.34 lb(s)
Height Adjustable	N/A
Slope	N/A
Chain Length	N/A
Wire Length	N/A
Canopy Width	N/A
Canopy Height	N/A
Canopy Length	N/A

Shipping

Carton Weight	0.42 lb(s)
Carton Width	4.72"
Carton Height	0.90"
Carton Length	13.78"
Carton Cubic Feet	N/A
Master Pack	20
Master Pack Weight	11.22 lb(s)
Master Pack Width	7.87"
Master Pack Height	9.84"
Master Pack Length	13.78"
Master Cubic Feet	N/A
UPS Shippable	Yes

Certification

Safety Rating	Dry
Energy Star	No
CA Title 24	No
CA Title 20	No
ADA	No

Other

UPC Code	845094050360
Material	Aluminum

Equivalents

Incandescent Watts	35.45
Fluorescent Watts	7.8

ET2 Contemporary Lighting and all designs, logos and images © 2014 ET2 Contemporary Lighting. All Rights Reserved. ET2 Contemporary Lighting reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes. Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.