



Product Specifications for E53850-AL

Job Name:	Job Type:
Quantity:	Comments



E53850-AL

CounterMax MX-LD-R LED Disc Add-On

This LED Add-On Disc must be used with a Starter Kit (E53853). No more than three LED Add-On Discs can be added to a single Starter Kit. Each LED Add-On Disc includes a 36" connection cord. Uses MXInterLink6 accessories. Click [here](#) for a complete list of compatible accessories.

Finish

Brushed Aluminum

Glass/Shade

Frosted

Product Category

Under Cabinet Disc

Lamping

Number of Bulb(s)	24
Light Type	LED
Bulb Type	LED
Max Bulb Wattage	0.1
Max Fixture Wattage	2.4
Rated Life	±30,000 Hours
Rated Lumens	±186
Color Temp	±3,000 K
Bulb(s) Included	Integrated
Light Up/Down	N/A
Beam Spread	N/A
CRI	N/A
Photo Cell Included	N/A
Ballast/Driver/Transformer	No
Dimmable	Optional Touch Dimmer

Measurements

Width	2.75"
Height	0.50"
Length	N/A
Extension	N/A
Back Plate Width	N/A
Back Plate Height	N/A
HCO	N/A
Min Overall Height	N/A
Max Overall Height	N/A
Hanging Weight	0.25 lb(s)
Height Adjustable	N/A
Slope	N/A
Chain Length	N/A
Wire Length	N/A
Canopy Width	N/A
Canopy Height	N/A
Canopy Length	N/A

Shipping

Carton Weight	0.28 lb(s)
Carton Width	3.35"
Carton Height	2.36"
Carton Length	4.41"
Carton Cubic Feet	N/A
Master Pack	100
Master Pack Weight	29.70 lb(s)
Master Pack Width	17.72"
Master Pack Height	13.00"
Master Pack Length	18.70"
Master Cubic Feet	N/A
UPS Shippable	Yes

Certification

Safety Rating	Dry
Energy Star	No
CA Title 24	No
CA Title 20	No
ADA	No

Other

UPC Code	845094050278
Material	N/A

Equivalents

Incandescent Watts	16.91
Fluorescent Watts	3.72

ET2 Contemporary Lighting and all designs, logos and images © 2014 ET2 Contemporary Lighting. All Rights Reserved. ET2 Contemporary Lighting reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes. Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.