

Product Specifications for E59912-SN					
	Job Name:	Job Type:			
ı					
	Quantity:	Comments			



## E59912-SN

## CounterMax MX-L120DC 7" 3000K 2-LED Under Cabinet

Uses MXInterLink4 accessories. Click  $\underline{\text{here}}$  for a complete list of compatible accessories.

<b>Finish</b> Satin Nickel		Glass/Shade Clear		<b>Product Category</b> Under Cabinet	
Lamping Number of Bulb(s)	2	<b>Measurements</b> Width	4.00"	Shipping Carton Weight	1.46 lb(s)
Light Type	LED	Height	1.00"	Carton Width	5.75 <sup>"</sup>
Bulb Type	Cree® LED	Length	7.00"	Carton Height	2.50"
Max Bulb Wattage	2.44	Extension	N/A	Carton Length	11.00"
Max Fixture Wattage	4.88	Back Plate Width	N/A	Carton Cubic Feet	N/A
Rated Life	±50,000 Hours	Back Plate Height	N/A	Master Pack	6
Rated Lumens	±200	НСО	N/A	Master Pack Weight	8.80 lb(s)
Color Temp	±3,000 K	Min Overall Height	N/A	Master Pack Width	11.42"
Bulb(s) Included	Integrated	Max Overall Height	N/A	Master Pack Height	6.69"
Light Up/Down	N/A	Hanging Weight	1.28 lb(s)	Master Pack Length	16.93"
Beam Spread	N/A	Height Adjustable	N/A	Master Cubic Feet	N/A
CRI	N/A	Slope	N/A	UPS Shippable	Yes
Photo Cell Included	N/A	Chain Length	N/A		
Ballast/Driver/Transformer	Yes	Wire Length	N/A		
Dimmable	Lutron® or Leviton® LED Dimmer	Canopy Width	N/A		
		Canopy Height	N/A		
		Canopy Length	N/A		
Certification		Other		Equivalents	
Safety Rating	Dry	UPC Code	845094049739	Incandescent Watts	18.18
Energy Star	No	Material	N/A	Fluorescent Watts	4
CA Title 24	No				
CA Title 20	No				
ADA	No				

ET2 Contemporary Lighting and all designs, logos and images © 2014 ET2 Contemporary Lighting. All Rights Reserved. ET2 Contemporary Lighting reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes. Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.