

Lighting Your Life Since 1970

Product Specifications - 85128WSOI			
Job Name:	Job Type:		
Quantity:	Comments		



85128WSOI **Basix EE 9-Light Chandelier**

ENERGY STAR CERTIFIED

Finish Oil Rubbed Bronze

Glass/Shade Wilshire

Product Category

Multi-Tier Chandelier

Lamping

Lamping	
Number of Bulbs	g
Light Type	Fluorescent
Bulb Type	GU24
Max Bulb Wattage	13
Max Fixture Wattage	117
Rated Life	±10,000 Hours
Rated Lumens	±8,100
Color Temp	±2,700 K
Bulb(s)	Included
Light Up/Down	N/A
Beam Spread	N/A
CRI	N/A
Photo Cell Included	N/A
Ballast/Driver/Transformer	No
Dimmable	No

Measuremen	ts
Width	

Measurements	
Width	32.0"
Height	31.5"
Length	N/A
Extension	N/A
Back Plate Width	N/A
Back Plate Height	N/A
HCO	N/A
Min Overall Height	N/A
Max Overall Height	N/A
Hanging Weight	18.4 lbs
Height Adjustable	N/A
Slope	N/A
Chain Length	72"
Wire Length	180"
Canopy Width	N/A
Canopy Height	N/A
Canopy Length	N/A

Shinning

্	nipping	
С	arton Weight	18.4 lbs
C	arton Width	11'
С	arton Height	31"
C	arton Length	34"
C	arton Cubic Feet	6.53
N	laster Pack	1
N	laster Pack Weight	N/A
N	laster Pack Width	N/A
N	laster Pack Height	N/A
N	laster Pack Length	N/A
N	laster Cubic Feet	N/A
U	IPS Shippable	Yes

Certification		Other	
Safety Rating	Dry	UPC Code	783209085879
Energy Star	Yes	Shades Included	N/A
CA Title 24	Yes	Crystals Included	N/A
CA Title 20	No	Diffuser Included	N/A
ADA	No	Conversion Kit	N/A
Dark Sky	N/A	Material	N/A

Equivalents

Incandescent Watts	736
Fluorescent Watts	N/A

Maxim Lighting International and all designs, logos and images © 2013 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.