



Lighting Your Life Since 1970

Product Specifications - 89924SN

Job Name:	Job Type:
Quantity:	Comments:



89924SN

CounterMax MX-L120DC 21" 2700K 6-LED Under Cabinet

Uses MXInterLink4 accessories. Click [here](#) for a complete list of compatible accessories.

Finish

Satin Nickel

Glass/Shade

Clear

Product Category

Under Cabinet

Lamping

Number of Bulbs	6
Light Type	LED
Bulb Type	Luxeon® LED
Max Bulb Wattage	2.32
Max Fixture Wattage	13.89
Rated Life	±50,000 Hours
Rated Lumens	±426
Color Temp	±2,700 K
Bulb(s)	Integrated
Light Up/Down	N/A
Beam Spread	N/A
CRI	85
Photo Cell Included	N/A
Ballast/Driver/Transformer	No
Dimmable	Lutron® or Leviton® LED Dimmer

Measurements

Width	4.0"
Height	1.0"
Length	21.0"
Extension	N/A
Back Plate Width	N/A
Back Plate Height	N/A
HCO	N/A
Min Overall Height	N/A
Max Overall Height	N/A
Hanging Weight	3.3 lbs
Height Adjustable	N/A
Slope	N/A
Chain Length	N/A
Wire Length	N/A
Canopy Width	N/A
Canopy Height	N/A
Canopy Length	N/A

Shipping

Carton Weight	3.3 lbs
Carton Width	6"
Carton Height	3"
Carton Length	25"
Carton Cubic Feet	0.23
Master Pack	6
Master Pack Weight	21.6 lbs
Master Pack Width	16.9"
Master Pack Height	6.7"
Master Pack Length	24.8"
Master Cubic Feet	1.63
UPS Shippable	Yes

Certification

Safety Rating	Dry
Energy Star	No
CA Title 24	No
CA Title 20	No
ADA	No
Dark Sky	N/A

Other

UPC Code	783209009639
Shades Included	N/A
Crystals Included	N/A
Diffuser Included	N/A
Conversion Kit	N/A
Material	N/A

Equivalents

Incandescent Watts	N/A
Fluorescent Watts	N/A

Maxim Lighting International and all designs, logos and images © 2013 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.