

LOW-VOLTAGE PENDANTS

Sky Pendant



DESCRIPTION

Lightweight anodized metal pendant. Available in 8" or 12" diameter. Includes low-voltage, 50 watt MR16 flood lamp or 8 watt replaceable 500 lumen 80 CRI 3000K LED SORAA® module and six feet of field-cutttable suspension cable.

INSTALLATION


Socket terminates with FreeJack male connector, which may be installed into a system connector. Elements ordered with a system prefix include a connector for that system.

ACCESSORIES & OPTICAL CONTROLS

Swag Hook

WEIGHT

1.45lb / 0.66kg ±



SIZE	D	H
SKY 8" 12"	8" (203 MM)	4" (102 MM)
SKY 12" 24"	12" (305 MM)	6" (152 MM)

copper



copper



satin nickel

ORDERING INFORMATION

700	SYSTEM	SKY	SHAPE OR SIZE	COLOR	FINISH	LAMP
FJ	FREEJACK		12 12" DIAMETER	CP COPPER	Z ANTIQUE BRONZE	12 VOLT HALOGEN
K	KABLE LITE		08 8" DIAMETER	SN SATIN NICKEL	C CHROME	-LEDS830 12 VOLT LED 80 CRI 3000K
MP	MONOPOINT				S SATIN NICKEL	-24 24 VOLT HALOGEN
MO	MONORAIL					
MO2	TWO-CIRCUIT MONORAIL					

Note: Note: MP includes 4" Round Flush Canopy.

Antique Bronze is not available for Kable Lite.

When installing LED option on MO2 only magnetic transformers may be used.



7400 Linder Avenue T 847.410.4400
Skokie, Illinois 60077 F 847.410.4500

Tech Lighting, L.L.C.

700 ____ SKY _____

FIXTURE TYPE: _____

JOB NAME: _____

NOTES: _____



©2015 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.